

TR-DCV1A4-XXV 直流電壓傳送器



勝特力材料 886-3-5753170
 勝特力电子(上海) 86-21-34970699
 勝特力电子(深圳) 86-755-83298787
[Http://www.100y.com.tw](http://www.100y.com.tw)

Measure Range	TR-DCV1A4-200MV : 0 - 200 mV * Isolated TR-DCV1A4 -2V : DC 0 - 2 DCV * Isolated TR-DCV1A4 -20V : 0 - 20 DCV * Isolated TR-DCV1A4 -200V :0 - 200 DCV * Isolated
Output	4 - 20 mA TR-DCV1A4-200MV : 0 mV DC = 4 mA , 100 mV DC= 12 mA , 200 mV DC= 20 mA TR-DCV1A4 -2V : 0 DCV = 4 mA ,1 DCV = 12 mA , 2 DCV = 20 mA TR-DCV1A4 -20V : 0 DCV =4 mA ,10 DCV = 12 mA , 20 DCV = 20 mA TR-DCV1A4 -200V : 0 DCV = 4 mA ,100 DCV = 12 mA , 200 DCV = 20 mA
External Adjustment	ZERO VR , SPAN VR
Power Supply	90 - 260 ACV/ 50 Hz/60 Hz
Operation Temperature	0 - 50 °C (32 - 122 °F)
Operation Humidity	Less than 80 %RH
Accessory Included	None
Optional Accessories	TR-DCV1A4-200MV :ST 50A/50mV , ST 100A/50mV , ST 1000A/50mV Orthrt None
Mounting	Din rail or Wall
Case	ABS plastic
Others	Two wires input