



Power Clamp Meter

Home > Products > DC/AC Power Clamp Meter > 3 Φ Power ClampNew Products **NEW**[Multimeter](#)[Clamp Meter](#)[Insulation tester](#)[Earth/ Ground Tester](#)[Milli / Micro Ohm Meter](#)**[Power Clamp Meter](#)**[Harmonic Clamp Meter](#)[Flexible Clamp Meter](#)[Calibrator](#)[Solar Power Meter](#)[Battery Impedance
Tester](#)[EMF Tester](#)[Anemometer/
Tachometer](#)[Thermometer](#)[Infrared Thermometer](#)[Humidity Temperature
Meter](#)[Light Meter](#)[Sound Level Meter](#)[Particle Counter](#)[CO/ CO₂ Tester](#)[PH Meter](#)[Lan Cable Tester](#)[Power Supply](#)[Accessories](#)

PROVA-6600 3 Φ Power Clamp

Product Features

- 3 f 4W, 3 f 3W, 3 f Balanced, 1 f 2W, and 1 f 3W Power Measurement.
- AC+DC true power, and True RMS AC Voltage and Current
- AC+DC 2000A, AC 600V, DC 800V
- AC+DC 1200KW(1 f), AC+DC 2000KW (3 f)
- Dual Display V+Hz, A+Hz, W+PF, KVA+KVAR, V+A
- Phase Angle Measurement
- 3 f RST(L1L2L3) Sequence Indication.
- Memory of 4 records.
- DCA/DCV Auto Zero when power clamp powering on.
- AC/DC Auto Detection.
- Auto range.

AC+DC True Power (PF 0.2-1.0, 3 Φ 3W, 3 Φ 4W, 1 Φ 2W, and 1 Φ 3W)

Range	Resolution	Accuracy(of rdg)	Input Range
0-99.9KW	0.1KW	+/- 2.0% +/- 0.05KW	AC 600V, DC 800V, ACA/DCA 2000A
100-999.9KW	0.1KW	+/- 2.0% +/- 0.5KW	AC 600V, DC 800V, ACA/DCA 2000A
1000-1200KW	1KW	+/- 2.0% +/- 5KW	AC 600V, DC 800V, ACA/DCA 2000A

AC+DC True Power (Power Factor 0.2-1.0, 3 Φ Balanced Power)

Range	Resolution	Accuracy (or rdg)	Input Range
0-99.99KW	0.01KW	+/- 2.0% +/- 0.5KW	AC 600V, DC 800V, ACA/DCA 2000A
100-999.9KW	0.1KW	+/- 2.0% +/- 0.5KW	AC 600V, DC 800V, ACA/DCA 2000A
1000-1200KW	1KW	+/- 2.0% +/- 5KW	AC 600V, DC 800V, ACA/DCA 2000A

POWER FACTOR (PF)

PF=KW/KVA

AC+DC Voltage (True RMS, Crest Factor<4, Autorange, Overload Protection 800VAC for all ranges)

Range	Resolution	Accuracy(of reading)		Input Impedance
		DC, 50/60Hz	40-400Hz	
0-200A	0.1V	+/- 1.5% +/- 5 dgts	+/- 2.0% +/- 5 dgts	10M Ω
200-500A	0.1V	+/- 1.5% +/- 5 dgts	+/- 2.0% +/- 5 dgts	10M Ω
500-600VAC	1V	+/- 1.5% +/- 5 dgts	+/- 2.0% +/- 5 dgts	10M Ω

200-500A	0.1A	+/- 2.0% +/- 5 dgts	+/- 2.5% +/- 5 dgts	AC 3000A
500-2000A	1A	+/- 2.5% +/- 5 dgts	+/- 3.0% +/- 5 dgts	AC 3000A

AC+DC KVA (Apparent Power)
(KVA)=VxA/1000
AC+DC KVAR (Reactive Power)
(KVAR)=

Phase Angle (must zero current reading before measurement)

Range	Accuracy	Sensitivity	Remark
50/60Hz	+/- 2.0 °	V>100V, A>10A	Zero Crossing Detection

Frequency (if<10 Hz, Hz=0)

Range	Accuracy	Sensitivity
50/60Hz	+/- 2dgts	V: >1V, A: >5A
10-400Hz	+/- 0.5% +/- 2dgts	V: >1A, A: >5A

General Specification

Conductor Size	Cable f 55mm. (approx.) Bus Bar 65mm(D)x24mm(W)
Battery Type	9V
Display	2x4 Digits Dual Display LCD
Range Selection	Auto
Overload Indication	OL
Power Consumption	28mA (approx.)
Low battery Indication	
Sampling Time	0.5 sec. (V and A) 1.6 sec. (W)
Operating Temperature	4 o to 50 o C
Operating Humidity	Less than 85% relative
Altitude	up to 2000M
Storage Temperature	-20 o C to 60 o
Storage Humidity	Less than 75% relative
Dimensions	271mm(L)x112mm(W)x46mm(H) 10.7"(L)x4.4"(W)x1.8"(H)
Weight	647g/22.8 oz (Battery included)

• BACK •

• INQUIRY •

© 2014 by TES Electrical Electronic Corp. All rights reserved. Tel:886-2-2799-3660 Fax:886-2-2799-3669 Add:7F, No. 31, Lane 513, Rui Guang
[About Us](#) | [News](#) | [Products](#) | [Application](#) | [Online Inquiry](#) | [Product Registration](#) | [Software](#) | [Contact Us](#) | [Jobs](#)